

330 to 520MHz - 6 TX Combiner

ITEM	SPECIFICATION
Model Number	UIY6TC330500AxxxxTxxxxNF
Frequency Range	330 ~ 520MHz
Frequency Separation	≥250 KHz
Tuning Range	5MHz
Insertion Loss	3.5 ~ 4.6dB
Isolation	65dB Min. @TX-TX 55dB Min. @ANT-TX
VSWR	1.25:1 Max. @Input 1.5:1 Max. @Output
Number of Channels	N Female @6xTX N Female @1xANT
Input Power	50W
Temperature Range	-10~ +65℃

Mechanical Drawing

